

Supported line types and PBXs

In the first column, find the type of line you will be recording, such as analog/radio, digital PBX and so forth. Find your phone set in second column and see in the third column which recording cards are compatible and with what options. Both D-channel and Vox recording are supported unless otherwise noted. The D-Channel option supports detecting PBX onhook/offhook, capture caller id, dialed #, lamps, buttons pressed, etc and is an option only available on digital lines.

Recorded Line type	Compatible phone sets	Compatible recording cards
Analog phone / radio lines	Any analog phone set	MOD-PCI-xxA / LDAxx-PCI
Digital PBX		
Alcatel 4200 / 4400	Reflex 4003, 4011, 4012, 4023, 4034 Reflex 4004 First Reflex 4010 Easy Reflex 4020 Premium Reflex 4035 Advanced Reflex 4039 Reflex 4059 PC Operator	MOD-PCI-xxP / NGXxx MOD-PCI-xxP / NGXxx MOD-PCI-xxP / NGXxx MOD-PCI-xxP / NGXxx MOD-PCI-xxP / NGXxx MOD-PCI-xxP / NGXxx MOD-PCI-xxP (vox only)
Ascom Ascotel 2020 (2 Wire)	Office 20, 25, 30, 35, 40 Office 45/45 Pro Office 130/130 Pro	MOD-PCI-xxP MOD-PCI-xxP MOD-PCI-xxP
Ascom Ascotel 2020 (4 Wire)	Crystal	MOD-PCI-xxP (vox only)
Aspect Telecom Call Center	Teleset 3010, 3190, 3192	MOD-PCI-xxP / NGXxx
Avaya Definity (2 Wire)	6210, 6218, 6220, 6221 6402, 6408, 8410, 8434 6402-D, 6408-D, 6416-D, 6424-D 8101, 8102, 8110, 8403, 8405, 8411, 8503, 8510, 8520, 8528 Call Master III, IV, V, VI 24xx series	MOD-PCI-xxP MOD-PCI-xxP / NGXxx MOD-PCI-xxP / NGXxx MOD-PCI-xxP MOD-PCI-xxP / NGXxx MOD-PCI-xxP
Avaya Definity (4 Wire)	7406, 8410 Call Master I, II, III, IV Call Master V 7303, 7305, 7401, 7403, 7405, 7406, 7407, 7410, 7434, 7444, 8101, 8102, 8110, 8403, 8405, 8410, 8411, 8434, 8503, 8510, 8520, 8527 94xx series	MOD-PCI-xxP / NGXxx MOD-PCI-xxP / NGXxx MOD-PCI-xxP MOD-PCI-xxP MOD-PCI-xxP
Avaya Definity (4 Wire) 5ESS extension	75xx series 8510 ISDN, 8520 ISDN, 8528 ISDN	MOD-PCI-xxP MOD-PCI-xxP
Avaya INDeX (SDX)	INDeX DT3 INDeX DT5 INDEX 2030 INDeX 2050	MOD-PCI-xxS / NGXxx MOD-PCI-xxS MOD-PCI-xxS / NGXxx NGXxx
Avaya IP Office	2410, 2420, 5410, 5420	NGXxx
Avaya Merlin	4400, 4400D, 4406D+, 4412D+, 4424D+, 4424LD+	MOD-PCI-xxP (vox only) / NGXxx
Avaya Magix (BRI)	MLX 5, 5D, 10, 10D, 20L, 28D	MOD-PCI-xxP (vox only) / NGXxx
Avaya S8300	2410, 2420	NGXxx
Bosch/Tenovis Integral 3 (4 Wire)	TB13, TE13, TH13, TM13, TS13	MOD-PCI-xxP (vox only) / NGXxx
Bosch/Tenovis Integral 5D (2 Wire)	T3 Classic, Comfort T3 Compact TB13, TE13, TH13, TM13, TS13, TH93, TH93C	NGXxx MOD-PCI-xxP MOD-PCI-xxP

Recorded Line type
Compatible phone sets
Compatible recording cards
Digital PBX

 Bosch/Tenovis Integral 55D
(2 Wire)

 T3 Classic
T3 Compact, Comfort
TB13, TE13, TH13, TM13, TS13, TH93,
TH93C

 MOD-PCI-xxP / NGXxx
MOD-PCI-xxP
MOD-PCI-xxP

EADS Intercom E

 ITE 12SD, 30SD
ITE 760
None specific

 NGXxx
NGXxx (vox only)
NGXxx

EADS Matra M6500

MC401, MC520, M7xx series

NGXxx

 EOn Millenium
eQueue

 -
501200-750, 501200-001, 501800-001
501600-001, 500600-750, 503000-001
503800-001

 NGXxx
NGXxx
NGXxx
NGXxx

Ericsson MD110/Business

 Dialog 2601, 2631, 2661, 2662, 3201,
3202, 3203, 3212, 3213, 4220, 4222, 4223,
4225
Dialog 2501, 2563, DBA 706
Operator Workstation, Console (OPI II),
Operator Console (OPI 3213)
Trader Panel CTT10, CTT11, TIU
Business Phone sets
DBC199

 MOD-PCI-xxP / NGXxx

NGXxx
MOD-PCI-xxP (vox only)
MOD-PCI-xxP (vox only)
MOD-PCI-xxP
MOD-PCI-xxP (vox only)

Fujitsu F9600

 F10B-0816-B001, F10B-0791-B001,
F10B-0794-B001, F10B-0789-B001,
F10B-0790-B001

NGXxx

Harris 2020

-

NGXxx

Inter-Tel Axxess

 550.4000, 550.4100, 550.4400,
550.8500, 550.8520, 550.8560
550.4300, 550.4500, 551.4400, 551.4100

 MOD-PCI-xxP / NGXxx

NGXxx

LG Aria

 LKD-2NS, LKD-8DS, LKD-30D,
LKD-30LD, LDP-7004D, LDP-7008D,
LDP-7016D, LDP-7024D, LDP-7024LD
LGP-xxx

MOD-PCI-xxP

LG Starex

LGP30D

NGXxx

Mitel SX200, SX 2000

 Superset 4001, 4015, 4025, 4150, 401+, 430
Superset 4125

 MOD-PCI-xxS / NGXxx
MOD-PCI-xxS

NEC Aspire

Model 0890041, 0890043, 0890045

MOD-PCI-xxP / NGXxx

NEC

DTP-32DA-1, DCU 60

NGXxx

Electra Elite, Professional

 DTP-8-1, 8D-1, 16-1, 32D-1
DTU-8-1, 16-1, 32-1, 8D-1, 8D-2, 16D-1,
32D-1, 32D-2
ETJ-8-2, 16DC-1, 16-2DD
DTP-32DE-1, 16D-1, 8-D
DTU-32D-2, 16-D-2

 MOD-PCI-xxP
MOD-PCI-xxP

MOD-PCI-xxP
MOD-PCI-xxP/ NGXxx
MOD-PCI-xxP/ NGXxx

NEC NEAX 1000

 DTP-8D, DCU 60
DTP-8-1, 8D-1, 16-1, 32D-1
DTU-8-1, 16-1, 32-1, 8D-1, 8D-2, 16D-1,
32D-1, 32D-2
ETJ-8-2, 16DC-1, 16-2DD
DTP-32DE-1, 16D-1, 8-D
DTU-32D-2, 16-D-2

 NGXxx
MOD-PCI-xxP
MOD-PCI-xxP

MOD-PCI-xxP
MOD-PCI-xxP
MOD-PCI-xxP

Recorded Line type
Digital PBX

NEC NEAX 2000, 2400

Compatible phone sets

 DTP-8-1, 8D-1, 16-1, 32D-1
 DTU-8-1, 16-1, 32-1, 8D-1, 8D-2, 16D-1,
 32D-1, 32D-2
 ETJ-8-2, 16DC-1, 16-2DD
 DTU-32D-2, 16-D-2
 DTP-16D-1, 8-D, DTP-32DE-1
 Dterm Series 3 (16 Button Display)
 DTP-32-DA-1
 DTR-8D1, 8-1, 32D-1, 2DT-1, 16D-1

Compatible recording cards

 MOD-PCI-xxP
 MOD-PCI-xxP

NEC Professional

 DTP-8-1, 8D-1, 16-1, 32D-1
 DTU-8-1, 16-1, 32-1, 8D-1, 8D-2, 16D-1,
 32D-1,
 ETJ-8-2, 16DC-1, 16-2DD
 DTP-32DE-1
 DTU-32D-2, 16-D-2
 DTP-32DA-1, 16D-1, 8-D
 DCU 60

 MOD-PCI-xxP
 MOD-PCI-xxP
 MOD-PCI-xxP / NGXxx
 NGXxx
 NGXxx
 NGXxx

 MOD-PCI-xxP
 MOD-PCI-xxP

 Nitsuko DX2E 32,
 DX2E i-series

 DX2E-12BTH, 16T-LC2
 DX2ET-12TXH, TXH, 24TSXH
 i-series

 MOD-PCI-xxP
 MOD-PCI-xxP
 MOD-PCI-xxP / NGXxx
 MOD-PCI-xxP / NGXxx
 NGXxx

 MOD-PCI-xxP
 MOD-PCI-xxP
 MOD-PCI-xxP (vox only)

Nortel DMS100

-

MOD-PCI-xxP / NGXxx

Nortel Meridian 1, SL100

 M2006, 2008, 2018, 2216, 2250, 2616,
 3901, 3902, 3903, 3904, 3905
 M2009, 2316, 3110, 3310, 3820
 M3820
 M2317

MOD-PCI-xxP / NGXxx

 MOD-PCI-xxP
 NGXxx
 NGXxx (vox only)

Nortel Norstar/BCM

 M7100, 7208, 7316, 7310, 7324
 M7410
 T7100, 7208, 7316

 MOD-PCI-xxP / NGXxx
 MOD-PCI-xxP
 MOD-PCI-xxP

Panasonic KX-TD

 KX-T 7431, 7453, 7630
 KX-T 72xx series
 KX-T 73xx series
 KX-T 74xx series
 KX-T 75xx series
 KX-T 76xx series
 KX-T 70xx series
 KX-T 77xx series

 MOD-PCI-xxP / NGXxx
 MOD-PCI-xxP
 MOD-PCI-xxP
 MOD-PCI-xxP
 MOD-PCI-xxP
 MOD-PCI-xxP
 MOD-PCI-xxP
 MOD-PCI-xxA
 MOD-PCI-xxA

Philips ISO3010

 D310/2, D320/2, D325/2/4, D330/4, D340/4
 D330/2, D340/2, D622/2, D623/2, D624/2,
 D320/4, D622/S, D623/S, D624/S

NGXxx

NGXxx

NGXxx (vox only)

Philips Sopho (2 Wire)

D310/2, D320/2, D325/2

MOD-PCI-xxP /

D330/2, D340/2

 NGXxx (vox only)
 MOD-PCI-xxP

Philips Sopho (4wire)

 D622S, 623S, 624S
 D310/4, D320/4, D325/4, D330/4, D340/4
 Sopho Operator Phone B630
 Sopho Console Model 60E

 MOD-PCI-xxP
 MOD-PCI-xxP
 MOD-PCI-xxP (vox only)
 MOD-PCI-xxP (vox only)

Rockwell Spectrum

-

MOD-PCI-xxP / NGX-xx (vox only)

Samsung DCS-828, Inforex

 DS-24SE-KTS, IDCS-8D, IDCS-18D
 IDCS-28D

 NGXxx
 NGXxx

Selta SAE

 Saefon CL08D, CL16D, LE, B, T, TK, E
 OP Attendant Console

MOD-PCI-xxP

MOD-PCI-xxP

Siemens

Optiset E Basic, Standard

MOD-PCI-xxP / NGXxx

Recorded Line type
Digital PBX

 Hicom100E/150E/300E/350E
 Hipath 3000/4000

Compatible phone sets

 OptiPoint 500 Entry, Economy, Basic,
 Standard, Advanced
 Optiset E Entry, Comfort / Advanced Plus,
 Conference, Memory
 AC 3.0, 4.0
 AC Win 3.0, 4.0
 Rolm Phone 240, 240E, 312L, 400, 624SL
 Advanced Conference DE
 Standard Conference DE

Compatible recording cards

MOD-PCI-xxP / NGXxx

MOD-PCI-xxP

 MOD-PCI-xxP (vox only)
 MOD-PCI-xxP (vox only)
 NGXxx
 NGXxx
 NGXxx

Siemens Rolm 9751 CBX

 Rolm Phone 120, 240, 240E, 312L, 400,
 624SL

NGXxx

Siemens Realitis DX (BRI)

D60, D70

NGXxx

Telrad IS

-

MOD-PCI-xxP (vox only)

Tadicom (Tadiran) Coral

 DKT-E 1110, 2311, 2321, 2322
 DKT2320
 DST-E
 FLEXSET 120 series
 FLEXSET 280 series

MOD-PCI-xxP

 NGXxx (vox only)
 MOD-PCI-xxP
 MOD-PCI-xxP
 MOD-PCI-xxP

Toshiba DK280

DKT2010, 2020

NGXxx

Toshiba Strata CTX670

 DKT 3010-SD, 3020-S, 3220, 2010SD
 2020, 2020SD, 2030SD

NGXxx

NGXxx

 DKT 2501, 2510, 2520, 3010, 3020,
 35xx series

MOD-PCI-xxP

VoIP PBX

3Com VCX

 3102
 3104
 IP Softphone

 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP

Alcatel OmniPCX (OXO/OXE)

 IP Touch 4018
 IP Touch 4028
 IP Touch 4038
 IP Touch 4068
 4010 IP e-Reflexes Easy / D351 IP
 4010 IP e-Reflexes Premium / D352 IP
 4010 IP e-Reflexes Advanced / D354 IP
 PIMphony (Basic / Pro / Team)
 4980 Softphone

 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP

Allworx 24xx

 9102
 9112
 X10 Softphone

 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP

Avaya IP Office

 4601 IP, 4602 IP
 4620 IP, 4625 IP
 4621 SW IP, 4622 SW IP, 4630 SW IP
 4690 Speakerphone
 5601 IP, 5602 IP, 5610 IP, 4520 IP

 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP

Cisco CallManager

 7902G, 7905G, 7910G, 7912G
 7940G, 7960G, 7970G, 7971G-GE
 7920 Wireless
 H323 / H225

 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP

Ericsson MD110/MX-One

 Dialog 4420 IP Basic, Dialog 4422 IP Office
 Dialog 4425 IP Vision

 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP

Mitel 3300 MX/LX

 5201 IP, 5207 IP, 5230 IP, 5235 IP, 5240 IP
 5215 IP (Dual Mode), 5220 IP (Dual Mode)

 SMOD-PCI-xxVOIP
 SMOD-PCI-xxVOIP

Recorded Line type	Compatible phone sets	Compatible recording cards
VoIP PBX		
NEC-Phillips NEAX/IPS/IPC/S/IV	Dterm IP / ITR 4D Dterm IP / ITR 8D Dterm IP / ITR 16D/16LD Dterm IP / ITR 32D	SMOD-PCI-xxVOIP SMOD-PCI-xxVOIP SMOD-PCI-xxVOIP SMOD-PCI-xxVOIP
Nortel BCM/M1/Succession	IP Phone 2001, 2002, 2004, 2008, 2010 USB Headset Adapter for IP Softphones IP Phone 1120E, 1140E IP Audio Conference Phone 2033 IP Softphone 2050 Mobile Voice Client 2050 WLAN Handset 2210, 2211	SMOD-PCI-xxVOIP SMOD-PCI-xxVOIP (vox only) SMOD-PCI-xxVOIP SMOD-PCI-xxVOIP SMOD-PCI-xxVOIP SMOD-PCI-xxVOIP SMOD-PCI-xxVOIP
Selta SAE	SAEFON CLI76D	SMOD-PCI-xxVOIP
Shoretel 40/8 Voice Switch	230 560	SMOD-PCI-xxVOIP SMOD-PCI-xxVOIP
Siemens Hicom/HiPath	optiPoint 410 economy optiPoint 420 economy optiPoint 420 standard optiPoint 420 advance	SMOD-PCI-xxVOIP SMOD-PCI-xxVOIP SMOD-PCI-xxVOIP SMOD-PCI-xxVOIP
SIP	-	SMOD-PCI-xxVOIP
VoIP Vox	-	SMOD-PCI-xxVOIP
T1/E1/ISDN PRI lines	-	MOD-PCI-xxT1/E1, DPxx
ISDN BRI lines	-	MOD-PCI-xxP